

ICOM

COMMUNICATIONS RECEIVER

IC-R6

## A Diverse and Flexible Wideband Scanner



**100 kHz — 1309.995 MHz Wideband Coverage\***

\* Frequency range depends on version. Cannot decode digital modes.

**Fast Scanning Speed —**

**100 Channels per Second\*** \* VFO mode.

**1300 Memory Channels with  
PC Programmable Capability**

**Wide Variety of Scan Types for  
Searching New Stations**

**Compact, Drip-Resistant Construction  
with Large Internal Speaker**

**15 Hours of Continuous Receive Capability\***

\* With rechargeable Ni-MH cells (1400 mAh x 2) using 50 mW external speaker.

OTHER FEATURES

- Built-in audio low pass filter
- ±1.0ppm high frequency stability (at 25°C)
- Earphone cord antenna for AM aviation as well as FM broadcast
- Ferrite bar antenna for AM broadcast
- 150mW loud audio with internal speaker
- DTCS and CTCSS tone squelch and reverse tone squelch
- Priority watch function with priority beep function
- Optional CT-17, CI-V level converter for remote control
- PC programmable with optional CS-R6
- Receiver-to-receiver cloning (optional OPC-474 required)
- Auto power OFF (0.5–2 hours and end of busy signal)
- Compact, drip-resistant construction
- Duplex operation monitoring
- Automatic LCD backlight
- Dial speed acceleration

- Built-in RF attenuator
- Auto memory write scan stores the detected frequency, mode and tone into a specified memory
- Reversible up/down buttons and dial knob for volume, frequency, memory channel, scan direction and set mode settings
- Optional new tube earphone, SP-27
- Weather channel receive with weather alert (USA version only)

SPECIFICATIONS

GENERAL

- Frequency coverage : 0.100–1309.995MHz\*  
(\* Cellular blocked in the U.S.A. version.)  
France 0.100–29.995, 50.200–51.200, 87.500–107.995, 144–146, 430–440, 1240–1300MHz
- Mode : AM, FM, WFM
- No. of memory channels : 1300 regular, 50 scan edges and 200 auto memory write
- Usable temperature range : -10°C to +60°C ; +14°F to +140°F
- Frequency stability : ±1.0ppm (at 25°C)
- Tuning steps : 5, 6.25, 8.33\*, 9\*, 10, 12.5, 15, 20, 25, 30, 50, 100, 125, 200kHz  
(\* Selectable depending on operating bands.)
- Battery requirement : 2×R6 (AA) size Ni-MH or alkaline cells
- External power supply : 4.5V DC rated (4.5–6.3V with BC-196SA/SD, CP-18A/E)
- Current drain Rated audio : 130mA typ. (Ext. SP, backlight off)  
at 3.0V DC Standby : 65mA typ.  
Power save : 30mA typ. (1:4 duty)
- Antenna impedance : 50Ω (SMA)
- Dimensions (W×H×D) : 58×86×29.8 mm;  
(Projections not included) 2<sup>9</sup>/<sub>32</sub>×3<sup>3</sup>/<sub>16</sub>×1<sup>1</sup>/<sub>16</sub> in
- Weight (approx.) : 200g; 7.1oz

RECEIVER

- Intermediate frequencies :  
FM, AM 266.7MHz, 19.65MHz, 450kHz  
WFM 266.7MHz, 19.95MHz, 750kHz
- Sensitivity (except spurious points):  
FM 1.625MHz– 4.995MHz 0.32μV typ.  
(12dB SINAD) 5.000MHz– 29.995MHz 0.25μV typ.  
30.000MHz– 117.995MHz 0.18μV typ.  
118.000MHz– 246.995MHz 0.18μV typ.  
247.000MHz– 469.995MHz 0.18μV typ.  
470.000MHz– 832.995MHz 0.32μV typ.  
833.000MHz–1029.995MHz 0.28μV typ.  
1030.000MHz–1309.995MHz 0.35μV typ.  
WFM 76.000MHz– 108.000MHz 1.1μV typ.  
(12dB SINAD) 175.000MHz– 221.995MHz 1.1μV typ.  
470.000MHz– 770.000MHz 1.8μV typ.  
AM 0.495MHz– 4.995MHz 1.3μV typ.  
(10dB S/N) 5.000MHz– 29.995MHz 0.89μV typ.  
118.000MHz– 136.000MHz 0.63μV typ.  
222.000MHz– 246.995MHz 0.63μV typ.  
247.000MHz– 329.995MHz 0.79μV typ.
- Selectivity AM, FM : More than 12kHz/–9dB,  
Less than 30kHz/–60dB  
WFM More than 150kHz/–6dB

- AF output power (at 3.0V DC, 10% distortion) :  
Internal speaker (16Ω load) More than 150mW  
External speaker (8Ω load) 80mW typ.
- External SP connector : 3-conductor 3.5 (d) mm (1/8")/8Ω

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810 F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Humidity	507.4	–
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard	
Water	IPX2 (Drip resistant)

Supplied accessories


- Ni-MH cells\* ● AC adapter, BC-196SA/SD\*
  - Antenna ● Belt clip ● Handstrap
- (\* Not supplied depending on version)

All stated specifications are subject to change without notice or obligation.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

- **BC-196SA/SD AC ADAPTER**  
4.5V DC, 400mA output. Allows you to power the IC-R6 and charge the supplied Ni-MH battery cells installed in the IC-R6 in 15 hours (approx.). For exclusive use with the IC-R6 and BC-194 only.
- **BC-194 CHARGER STAND**  
Drop-in charger for use with BC-196S or CP-18A/E.
- **CP-18A/E CIGARETTE LIGHTER CABLE**  
6V DC, 1.5A output from 12V cigarette lighter socket.
- **HP-4 HEADPHONE**  
Light weight monaural headphone.
- **SP-13 EARPHONE**  
**SP-27 TUBE EARPHONE**  
Provides clear audio even in noisy environments.
- **LC-146A CARRYING CASE**  
Helps protect the receiver from scratches, etc.
- **CT-17 CI-V LEVEL CONVERTER**  
For receiver remote control from a PC.
- **CS-R6 CLONING SOFTWARE**  
**OPC-478 CLONING CABLE (RS-232C cable)**  
**OPC-478UC CLONING CABLE (USB cable)**  
Use a PC to easily edit stored memory channel data.
- **OPC-474 CLONING CABLE**  
Used for receiver-to-receiver data cloning.
- **AD-92SMA ANTENNA CONNECTOR ADAPTER**  
Allows you to connect a BNC-type antenna.



Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries. All other trademarks are the properties of their respective holders.

Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 www.icom.co.jp/world

Count on us!

Icom America Inc.

12421 Willows Road NE  
Kirkland WA 98034  
Phone: +1 (425) 454-8155  
Fax: +1 (425) 454-1509  
E-mail: sales@icomamerica.com  
URL: http://www.icomamerica.com

Icom New Zealand

146A Harris Road, East Tamaki,  
Auckland, New Zealand  
Phone: +64 (09) 274 4062  
Fax: +64 (09) 274 4708  
E-mail: inquiries@icom.co.nz  
URL: http://www.icom.co.nz

Icom (UK) Ltd.

Blacksole House, Altrix Park,  
Herne Bay, Kent, CT6 6GZ, U.K.  
Phone: +44 (01227) 741741  
Fax: +44 (01227) 741742  
E-mail: info@icomuk.co.uk  
URL: http://www.icomuk.co.uk

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,  
Taipei, Taiwan, R.O.C.  
Phone: +886 (02) 2559 1899  
Fax: +886 (02) 2559 1874  
E-mail: sales@asia-icom.com  
URL: http://www.asia-icom.com

Icom Canada

Glenwood Centre #150-6165 Highway 17,  
Delta, B.C., V4K 5B8, Canada  
Phone: +1 (604) 952-4266  
Fax: +1 (604) 952-0090  
E-mail: info@icomcanada.com  
URL: http://www.icomcanada.com

Icom (Europe) GmbH

Communication Equipment  
Auf der Krautweide 24  
65812 Bad Soden am Taunus, Germany  
Phone: +49 (6196) 76685-0  
Fax: +49 (6196) 76685-50  
E-mail: info@icomeurope.com  
URL: http://www.icomeurope.com

Icom France s.a.s.

Zac de la Plaine,  
1 Rue Brindejonc des Moulinais, BP 45804,  
31505 Toulouse Cedex 5, France  
Phone: +33 (5) 61 36 03 03  
Fax: +33 (5) 61 36 03 00  
E-mail: icom@icom-france.com  
URL: http://www.icom-france.com

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding  
Road, Haidian District, Beijing, 100039, China  
Phone: +86 (010) 5889 5391/5392/5393  
Fax: +86 (010) 5889 5395  
E-mail: bjicom@bjicom.com  
URL: http://www.bjicom.com

Your local distributor/dealer:

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,  
Clayton, VIC 3168 Australia  
Phone: +61 (03) 9549 7500  
Fax: +61 (03) 9549 7505  
E-mail: sales@icom.net.au  
URL: http://www.icom.net.au

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"  
Bajos A 08174, Sant Cugat del Valles,  
Barcelona, Spain  
Phone: +34 (93) 590 26 70  
Fax: +34 (93) 589 04 46  
E-mail: icom@icomspain.com  
URL: http://www.icomspain.com

Icom Polska

81-850 Sopot, ul. 3 Maja 54, Poland  
Phone: +48 (58) 550 7135  
Fax: +48 (58) 551 0484  
E-mail: icompolska@icompolska.com.pl  
URL: http://www.icompolska.com.pl